

Total number of printed pages-4

53 (EC 501) ELWV

2018

**ELECTROMAGNETIC WAVES**

Paper : EC 501

Full Marks : 100

Time : Three hours

**The figures in the margin indicate full marks for the questions.**

Answer **any five** questions.

5×20=100

1. (a) Write down Maxwell's equations for time varying electromagnetic fields when the media is homogeneous source free lossless, isotropic and linear.
- (b) Obtain an expression of wave equation of a conducting medium.
- (c) What do you mean by Perfect Conductor ?
- (d) Explain Maxwell's fourth equation of modified Ampere's circuital law. What is displacement Current ?

5+6+3+6

Contd.

2. (a) Prove that the electric field at a point ( $r > a$ ) due to a uniformly charged sphere of radius 'a' is the same as the whole charge located at the centre of the sphere.

(b) A circular disk of radius 'a' uniformly charged with  $P_s \text{ C/m}^2$ : If the disc lies on the  $z = 0$  plane with its along the z-axis

(i) Show that at point (0,0,h)

$$E = \frac{P_s}{2 \epsilon_0} \left\{ 1 - \frac{h}{[h^2 + a^2]^{1/2}} \right\} a_z$$

(ii) From this derive the E field due to an infinite sheet of charge on the  $z=0$  plane.

(iii) If  $a \ll h$ , show that E is similar to the field due to a point charge.

9+11

3. (a) What is meant by the uniform plane wave? Derive the wave equation in terms of electric and magnetic fields.

(b) Derive Poynting theorem and explain clearly every term. Calculate power flow for a plane wave.

(3+7)+(6+4)

4. (a) Derive an expression for the input impedance  $Z_{in}$  of a lossless transmission line, in terms of relevant Parameters, when the line is terminated into impedance  $Z_L$ .
- (b) Show that for a lossless transmission line the input impedance of a line repeat over every  $\lambda/2$  distance.
- (c) At frequency of 80MHz, a lossless transmission line has a characteristic impedance of  $300\Omega$  and a wavelength of 2.5m. Find the value of  $L$  and  $C$ .
- 8+5+7
5. (a) What does a lossless and distortionless line mean ?
- (b) Derive the necessary condition for a transmission line to become a distortion less line.
- (c) Prove that a distortion less line is not necessarily a lossless line but a lossless line is a distortion less line.

- (d) An airline has characteristic impedance of  $70\Omega$  and phase constant  $3\text{rad/m}$  at  $100\text{MHz}$ . Calculate the inductance per meter and the capacitance per meter of the line.

4+8+3+5

6. (a) Establish the boundary conditions for electric and magnetic field intensities in the interface between two dielectric media.

- (b) Explain how these conditions will be modified, if one of the media is a perfect conductor.

- (c) If  $x < 0$  defines region 1 and  $x > 0$  defines region 2, then find the electric field intensity in region 2 ( $\epsilon_{r2} = 5$ ), if electric field intensity in region 1 ( $\epsilon_{r1} = 1$ ) is

$$E_1 = (4\hat{u}_x + 1.5\hat{u}_y - 2\hat{u}_z)\text{V/m}$$

7+6+7

7. Short notes on : **(any four)** 4×5=20

- (i) Skin depth
- (ii) Ampere's Circuital Law
- (iii) Smith Chart
- (iv) Poynting Theorem
- (v) Conduction and Convection Current.