


2024



SIGNALS AND SYSTEMS

Full Marks: 100

Time: Three hours

*The figures in the margin indicate full marks for the questions.**Answer any five questions.*

1.	a)	Find the output of an LTI system, when the input to the LTI system is a complex exponential (eigen-function of the system) given by $x(t) = e^{t'}$.	10
	b)	Find the even and the odd components of the signal: $x(t) = \cos\left(\omega_0 t + \frac{\pi}{3}\right)$.	10
2.	a)	If the input applied to an LTI system with impulse response ' $h(t)$ ' is ' $x(t)$ ', deduce the output ' $y(t)$ ' from the LTI system.	5
	b)	Find the result of the convolution of two identical pulse of amplitude ' A '. What will be the result of two non-identical pulses shown in the figure? 	2+3 = 5
	c)	Find the convolution of the two functions: $s(t) = 3\cos(2t)$; for all ' t ' and $h(t) = \begin{cases} e^{-t}; & t \geq 0 \\ e^{+t}; & t < 0 \end{cases}$.	10
3.	a)	In the given figure, find the continuous-time Fourier series (CTFS) representation of ' $S(t)$ ':	8+2 = 10

		 <p>Hence, show that only the odd harmonics of the series exist.</p>	
	b)	Find the Fourier transform of a rectangular pulse $\Pi\left(\frac{t}{\tau}\right)$; where ' τ ' is the pulse width of the pulse. Hence find the zero crossings of the spectrum of the rectangular pulse.	6+4 = 10
4.	a)	<p>In the RL circuit shown below, a unit step input voltage '$V = u(t)$' is applied with all initial conditions assumed to be zero.</p>  <p>Using Laplace transform, find the current through the circuit. Find the voltage across the resistance and the inductance. Hence plot the voltage across the resistance and the inductance.</p>	5+2+3 = 10
	b)	<p>The circuit given below is initially in the steady state with the switch 'S' open. The switch is closed at $t = 0$.</p> <p>i) Find $V_c(t)$.</p> <p>ii) Determine the final value of '$V_c(t)$' and verify it from the final value of Laplace transform.</p>	7+3 = 10

5.	a)	What are band-limited signals? State the sampling theorem for a low-pass band-limited signal. Hence show that the spectrum of sampled waveform, in case of impulse sampling, is the repetition of the spectrum of low-pass band-limited signal.	1+2+12 = 15
	b)	Calculate the Nyquist rate and the Nyquist interval for $x(t) = 1 + \cos(2000 \times \pi \times t) + \sin(4000 \times \pi \times t)$.	5
6.	Write short notes on <i>any two</i> from the following:		10+10 = 20
	a)	BIBO stability of LTI system.	
	b)	DC component of a signal using the polar form representation of the Fourier series.	
	c)	Fourier transform of signum function.	
	d)	Transfer function of a Zero-Order Hold (ZOH) circuit.	

XXXXXXXX